

**OMNITRONIC GNOME-202 Mini mixer**

2-channel DJ mixer in miniature design

- Super portable and lightweight DJ mixer
- 2 stereo channels with gain control and 2-band EQ, RCA connectors
- Adjustable microphone input/headphones output via 6.3 mm jack
- Adjustable master output and record output via RCA connectors
- Anodized aluminum housing



**Technical specifications:**

Power supply:	230 V AC, 50 Hz ~ via supplied power unit
Power consumption:	6 W
Line input:	2 x stereo RCA
Microphone input:	6.3 mm jack, unbal.
Master output:	stereo RCA
Record output:	stereo RCA
Headphones output:	6.3 mm stereo jack
Frequency range:	20-20000 Hz
S/N ratio:	>85 dB
Distortion:	<0.5 %
Dimensions (LxWxH):	165 x 100 x 60 mm
Weight:	500 g

- No. 10006880.....black
- No. 10006881.....silver
- No. 10006882.....gold
- No. 10006883.....red
- No. 10006884.....green



**OMNITRONIC EMX-5 5-channel club mixer**

Professional 5-channel club mixer

- Inputs: 6 x line, 2 x phono/line, 2 x mic
- Gain control and 3-band equalizer per channel
- 1 DJ microphone channel with talkover
- XLR outputs



No. 10006770

**Technical specifications:**

Power supply:	230 V AC, 50 Hz ~, via supplied power unit
Power consumption:	30 W
Inputs:	
DJ MIC (front):	combined XLR (3-pin)/ 6.3 mm jack (1/4") (bal.)
MIC 1,2 (rear):	6.3 mm jack (1/4") (bal.)
Impedance:	1 kohms
Minimum input voltage:	1.5 mV RMS
LINE 1-5:	stereo RCA
Impedance:	27 kohms
Minimum input voltage:	150 mV RMS
PHONO 1,2:	stereo RCA
Impedance:	47 kohms
Minimum input voltage:	3 mV RMS
Outputs:	
MASTER:	stereo RCA, stereo XLR (3-pin)
ZONE:	stereo RCA
Impedance:	400 ohms
Output voltage:	1 V RMS/ 0 dB
REC:	stereo RCA
Impedance:	5 kohms
Output voltage:	225 mV RMS
Dimensions (WxHxD):	483 x 179 x 94 mm (19", 4 U)
Weight:	4 kg