# SMP 12.22

00151

## Beschreibung

Sehr rauscharmes 12-Kanal PA-Mischpult.

## Funktionen

- Sehr rauscharmes 12-Kanal PA-Mischpult.
- 2 Untergruppen (ALT 3-4 bus)
    - Eingebauter 24 Bit DSP Effektgerät mit 100 Voreinstellungen & Fußschalter Eingang
    - **USB Ein-/Ausgang für direkte Aufzeichnung auf PC**
    - 6 symmetrische Eingangskanäle, 4 Mono + 4 Stereo:
    - Eingangsverstärkung
    - Inserts auf Monokanälen
    - Spitzenanzeige @ -5dB
    - Hochpassfilter @ 75Hz
    - 3-Band-Equalizer
    - 1 AUX Send mit Pre(vor)/Post(nach)-Schalter
    - EFX Send für Effekteeinheit (post)
    - PAN/BAL Regler
    - Kombinierte Kanal mute/ALT3-4 Subgruppenschalter Taste
    - PFL-Schalter
    - LEVEL mit 60 mm Faderregler
- 48 V Phantomspeisung auf allen symmetrischen Mikrofoneingängen
- Verwendung von externen Effekten möglich
- Symmetrische Main L/R ausgangsregler
- Kopfhörer und Kontrollraumausgang
- 2x 10 Feld LED Volumenmesser
- Externer Leistungstransformator
- 19” Stützen für einfachen Rack-Einbau einbegriffen
- Kostenlose recording-Software zur Verfügung: Audacity: http://www.audacityteam.org/

SYNQ AUDIO RESEARCH

www.synq-audio.com | https://www.facebook.com/synq.audio/

*Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2015 by BEGLEC NV. All rights reserved.*

## Spezifikationen

| | |
|---|---|
| **Allgemein : Anwendung** | DJ & Club, Stage & Rental |
| **Allgemein : Abmessung (cm)** | 32.8 x 9 x 42 cm |
| **Allgemein : Gewicht (kg)** | 4.6 |
| **Allgemein : Netz/Batterie** | AC 230V, 50Hz |
| **Allgemein : Energie-label** | Nein |
| **Allgemein : Stromverbrauch W** | 36 |
| **Allgemein : Farbe** | black |
| **Allgemein : Schirm** | Nein |
| **Allgemein : Fixierung** | 19" rack mountable |
| **Allgemein : HE** | Nein |
| **Ton : min. frequenz (Hz)** | 20 |
| **Ton : max. frequenz (Hz)Ton : min. frequenz (Hz)** | 20000 |
| **beglec_attr_audsnratio** | Nein |
| **beglec_attr_audsensitivity** | Nein |
| **beglec_attr_audsupaudfor** | Nein |
| **beglec_attr_audsupaudmed** | Nein |
| **beglec_attr_audmaxchan** | 12 |
| **Anschluß : eingang** | Nein |
| **Anschluß : ausgang** | Nein |
| **Anschluß : XLR 3-polig** | Ja |
| **Anschluß : rca** | Ja |
| **Anschluß : jack** | Ja |
| **Anschluß : Power Conn.** | Nein |
| **Anschluß : midi** | Nein |
| **Anschluß : usb** | Ja |
| **Anschluß : wifi** | nee |
| **Anschluß : bluetooth** | Nein |
| **beglec_attr_funceq** | Ja |
| **beglec_attr_funcsoundfx** | Nein |
| **EANCode** | 5420025601511 |
| **Discontinued** | Nein |

**Max output level (0.5% thd @ 1kHz):**
+26dB (MAIN L/R)
+20dB (ALT 3/4, AUX/EFX, CTRL ROOM)
+20dB (INSERT)
More than 100mW (HEADPHONES) @33Ohm

**T.H.D:**
0.1% @ +14dB 20Hz~20kHz (MIX L/R, ALT 3/4, AUX/EFX SEND, CTRL ROOM) @10kOhm

**Frequency response:**
20Hz~20kHz, +1/-2dB (MIX L/R, ALT 3/4, AUX/EFX SEND, CTRL ROOM) @10kOhm

**Hum and Noise (average Rs=150Ohm):**
- 127dB equivalent input noise
- 95dB residual noise (MIX L/R, AUX SEND, EFX SEND, CTRL ROOM)
- 88dB (MIX L/R, AUX SEND, EFX SEND, CTRL ROOM) Master fader at nominal level and all channel volumes at minimum.

**Crosstalk (@ 1kHz):**
- 70dB between input channels
- 70dB between input/oputput channels

**Gain Control (mono input channel):**
44dB Variable (-50dB ~ -6dB) (-30dB ~ +14dB)

**Gain Control (combined mono/stereo input channel)**
40dB Variable (-20dB ~ +20dB)

**Input channel Equalization:**
HIGH: 12kHz shelving
MID: 2.5kHz peaking
LOW: 80Hz shelving
*Turnover/roll off frequencies: located 3dB below max. boost/cut

**LED Meters:**
2x 10 segment LED for MAIN L/R, ALT3/4, TAPE IN or PFL

**Phantom Power (balanced input):** +48V DC

**Internal Digital Effect:**
100 selectable presets FOOT Switch control (ON/OFF)

**Channel indicators:**
Peak: an indicator for each channel turns on when the pré-channel fader signal is 5dB below clipping

SYNQ® AUDIO RESEARCH

www.synq-audio.com | https://www.facebook.com/synq.audio/

*Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2015 by BEGLEC NV. All rights reserved.*